



PTR - 600

AM/FM Programmable Digital Tuner

This AM/FM Programmable Digital Tuner is Broadcast Quality. This sleek black tuner is compact enough to fit almost anywhere. It can also be rack mounted with an optional rack mount kit. The tuner delivers a clear crisp signal on the FM as well as the AM bands.



FEATURES

- AM/FM Digital Frequency Display
- PLL Quarts Synthesized Precision Tuning System
- 30AM and 30 FM Station Memory Presets
- Automatic Station Presetting
- Up/Down Station Memory Scan Function
- Digital Clock Display
- Programmable "Daily or Once" Automatic Turn-On Preset
- Programmable Automatic Shut-Off (Sleep)
- RDS - Radio Data System
- High Luminosity Digital Fluorescent Display
- Display Dimmer Function
- Rack Mounting with Optional Rack Shelf (2U)
- Remote Control not Available

SPECIFICATIONS

FM Tuner Section:

Tuner Range: 87.5 - 108 Mhz
Usable Sensitivity: (IHF) Mono=10 dbf
50 db Quieting: Stereo=33 dbf Mono=17 dbf
Selectivity: Alternate Channel (98 Mhz) 65 db
Image Response Ratio: 60 db
Frequency Response: 20 Hz - 15 KHz
Capture Ratio: 2 db at 98 Mhz
Distortion: At 65 dbf, 98 Mhz: Mono=0.2% Stereo=0.3%
Signal to Noise Ratio: At 65 dbf, 1KHz: Mono=70 db - Stereo=65 db
AM Suppression Ratio: 80 db
Stereo Separation: 40 db at 1 KHz
Output Level: 800 Mv at 2.2 K ohm

AM Tuner Section

Tuning Range: 530 - 1720 KHz - 10 KHz steps
Useable Sensitivity: 55 db/m
Selectivity: 55 db
Distortion: Mono=0.2% - Stereo=0.4%
Image Response Ratio: 35 db
IF Response Ratio: 60 db
Distortion: 1% at 85 db/m
Signal to Noise Ratio: 40 db at 85 db/m
Output Level: 220 mV at 2.2 K ohm

General

Antenna Impedance: 75 and 300 ohm
Power Requirement: 120v AC 50-60 Hz - 7 watt
Dimensions: 17 1/8" W - 3 1/2" H - 11 1/2" D
Finish: Matte Black
Net Weight: 6.5 lb



"Keep it Simple - Simply Stor-Com"

Stor-Com, Inc., 4553 Gateway Circle, P. O. Box 292153, Kettering OH 45429-2153

1-800-356-0368 Fax 1-937-428-9656

WWW.Stor-Com.com E-Mail Storcom@AOL.com